

SafeTac Portable 200 Amp DM1-2 Deadman Switch

DM1 – 1 (Single pole 300 amps) suit's inverters fitted with large dinse output plugs

DM1-2 (Dual pole 200 amps) suit's inverters with small dinse output plugs

- The DM1-2 is a dual pole (Both leads for total isolation) inline emergency isolation switch
- Isolation is achieved by pressing down on large red button
- Rated 200 amps 100% duty cycle
- Designed for use on Inverter welders fitted with small dinse plugs up to 200 amp rating.
- May also be used to isolate Lincoln LN25 work lead prior to connection or repositioning.
- Constructed from UV stabilized UHMPE
- 1 Metre x 25mm² input leads output is via dinse plugs
- Fitted With .5 Metre x 50mm carry strap
- Warranty 1 Year RTB



Size & weight: L220mm x W90mm x H130mm x 2Kgs
Shipping dimensions: L300mm x W150mm x H120mm x 2.4Kgs

www.safetac.com.au